



Frame Relay NC/NCI/SECNCI Combinations

Contents

Purpose	2
UNI	3
NNI	4
Change Log	5

Purpose

The purpose of the job aid is to provide commonly used NC/NCI/SECNCI combinations to assist with ordering of the Frame Relay product.

UNI

Service Description	NC	NCI	SECNCI
UNI Port with Access			
56Kbps UNI Port with Access	XH-R	04DU5.56 04DU9.1SN (CFA)	04DU9.1SN
56Kbps UNI	XH-G	04DU5.56	04DM5.E
64Kbps UNI Port With Access	XD-R	04DU5.64 04DU9.1SN (CFA)	04DU9.1SN
64Kbps UNI	XD-G	04DU5.64	04DM5.E
384Kbps UNI Port With Access	HCER	04DU9.1SN 04DS6.44 (CFA)	04DU9.1SN
1.536Mbps (1536Kbps) UNI Port With Access	HCER	04DU9.1SN 04DS6.44 (CFA)	04DU9.1SN
44.736 Mbps UNI	HF-D	04DS6.44	04CX6.3
44.736Mbps UNI (Sub rate)	HF-D	04DS6.44	04DS6.44
44.736Mbps UNI (Sub rate) (Un-Channelized, C-Bit)	HFCD	04DS6.44A	04DS6.44A
44.736Mbps UNI (Sub rate) (Channelized, C-Bit)	HFCD	04DS6.44I	04DS6.44I
UNI Port Only			
56K UNI Port Only	SNCA	04QC5.OOP	04CX9
64K UNI Port Only	SNCB	04QC5.OOQ	04CX9
128K UNI Port Only	SNCJ	04QB9.11	04CX9
384K UNI Port Only	SNCE	04QB9.11	04CX9
1.536M (1536K) UNI Port Only	SNCC	04QB9.11	04CX9

NNI

Service Description	NC	NCI	SECNCI
NNI Port Only			
1.536Mbps (1536Kbps) NNI Port Only (Co-location)	HCEO	04QB9.11	04CX9
1.536Mbps (1536Kbps) NNI Port Only	HCEO	04DU9.1SN 04DS6.44 (CFA)	04DU9.1SN
44.736 Mbps NNI Port Only (Co-location)	HF-E	04QB6.33	04CX6.3
44.736 Mbps NNI Port Only (Sub rate)	HF-E	04DS6.44	04DS6.44
44.736 Mbps NNI Port Only (Sub rate) (Un-Channelized, C-Bit)	HFCE	04DS6.44A	04DS6.44A
44.736 NNI Port Only (Sub rate) (Channelized, C-Bit)	HFCE	04DS6.44I	04DS6.44I

Change Log

Date	Page Number	Change