



UNE LSR Order Samples

New Linesharing Service

REQTYP: AB

ACT: N

Description: Establish New Linesharing Service

Field	Data Description	Field Entry
Local Service Request Form (LSR)		
CCNA	Customer Carrier Name Abbreviation	<ZTK>
PON	Purchase Order Number	<Your PON>
VER	Version	<01>
LOCQTY	Location Quantity	<001>
D/TSENT	Date and Time Sent	<200706080800>
DDD	Desired Due Date	<20070611>
REQTYP	Request Type	AB
SLI	Sub-Loop Indicator	S
ACT	Activity	N
AGAUTH	Agency Authorization Status	Y
ACTL	Access Customer Terminal Location	DLEC CLLI
TOS	Type of Service	2R2- (See Footnote 1)
NC	Network Channel Code	UAR-
NCI	Network Channel Interface Code	02QB9.00A
SECNCI	Secondary Network Channel Interface Code	02CU9.01A(See Footnote 4)
INIT	Initiator Identification	<Joe Smith>
TEL NO	Initiator Telephone Number	<8134833525>
IMPCON	Implementation Contact	<Mary Williams>
TEL NO	Telephone Number	<8134383000>
End User Form (EU)		
LOCNUM	Location Number	<001>
AFT	Address Format Type	<001>
NAME	End User Name	<Smith>
SANO	Service Address House Number	<330>
SASN	Service Address Street Name	<PHELPS>
SATH	Service Address Type	<DR>
CITY	City	<Anytown>
STATE	State/Province	<WV>
ZIP	Zip/Postal Code	<75038>
EATN	Existing Account Telephone Number	<3041231234>
Loop Service Form (LS)		
Administrative		
LQTY	Loop Quantity	<1>
Service Detail 1 (SD)		
LOCNUM	Location Number	<001>
LNUM	Line Number	<00001>
LNA	Line Activity	<N>
CKR	Circuit Reference	<>(See Footnote 2)
SLTN	Shared Line TN	<3041231234>
RelayRack	Relay Rack	<ZTK001> (See Footnote 3)
SHELF	Shelf	<02> (See Footnote 3)



UNE LSR Order Samples

New Linesharing Service

REQTYP: AB

ACT: N

Description: Establish New Linesharing Service

Field	Data Description	Field Entry
SLOT	Slot	<001> (See Footnote 3)
Footnotes		
1. Refer to Business Rules for TOS guidelines and requirements.		
2. Optional. CLEC Circuit Reference Assigned		
3. Relay Rack/Shelf/Slot utilized in Flag=L properties. Shelf/Slot only are used in Flag=F properties.		
4. Secondary Network Channel Code (SEC NCI) is applicable in Flag=L properties		