



## UNE LSR Order Samples

Partial Loop Disconnect Including BTN

REQTYP: AB

RPON# 1 = ACT: C

RPON# 2 = ACT: N

Description: Partial Loop disconnect from multiline account that includes disconnect of the BTN \*Requires RPON

| Field  | Data Description                   | Field Entry                               |
|--|------------------------------------|---|
| <b>RPON #1 Disconnect Circuits including BTN</b> |                                    |   |
| <b>LSR Form</b>                                  |                                    |   |
| CCNA   | Customer Carrier Name Abbreviation | <ZTK>                                     |
| PON  | Purchase Order Number              | <Your PON>                                |
| VER  | Version                            | <01>                                      |
| LOCQTY   | Location Quantity                  | <001>                                     |
| DDD  | Desired Date Due                   | <20160612>                                |
| REQTYP   | Request Type                       | AB  |
| SLI  | Sub Loop Indicator                 | S   |
| ACT  | Activity                           | C   |
| AGAUTH   | Agency Authorization Status        | Y   |
| ACTL   | Access Customer Terminal Location  | <CLEC CLLI>                               |
| LSO  | Local Serving Office               | <562325>                                  |
| TOS  | Type of Service                    | <12F1> (See Footnote 1)                   |
| NC   | Network Channel Code               | LX-- (See Footnote 2)                     |
| NCI  | Network Channel Interface Code     | 02QC2.OOF (See Footnote 2)                |
| <b>NOR</b>                                       | <b>Number of Requests</b>          | <b>0102 (See Footnote 4)</b>              |
| <b>RPON</b>                                      | <b>Related Pon</b>                 | <b>sample1 (See Footnote 4)</b>           |
| <b>RPVER</b>                                     | <b>Related Pon Version</b>         | <b>01 (See Footnote 4)</b>                |
| INIT   | Initiator Name                     | <Initiator Name>                          |
| TEL NO   | Initiator Telephone Number         | <9192257998>                              |
| <b>EU Form</b>                                   |                                    |   |
| LOCNUM   | Location Number                    | <001>                                     |
| NAME   | End User Name                      | <Our Business Rules>                      |
| AFT  | Address Format Type                | <N if normal, C if assigned house number> |
| SANO   | Service Address Number             | <14917>                                   |
| SASN   | Service Address Street Name        | <Musketeer>                               |
| SATH   | Service Address Street Type        | <RD>                                      |
| CITY   | City                               | <Anytown>                                 |
| STATE  | State/Province                     | <CA>                                      |
| ZIP  | Zip/Postal Code                    | <12345>                                   |
| EATN   | Existing Account Telephone Number  | <2090619999>                              |
| LCON   | Local Contact                      | <Jane Doe>                                |
| TEL NO   | Local Contact Telephone Number     | <5623259999>                              |
| <b>LS Form</b>                                   |                                    |   |
| <b>Administrative</b>                            |                                    |   |
| LQTY   | Loop Quantity                      | <1>                                       |
| <b>Service Detail (SD1)</b>                      |                                    |   |
| LOCNUM   | Location Number                    | <001>                                     |
| LNUM   | Line Number                        | <00001>                                   |



## UNE LSR Order Samples

Partial Loop Disconnect Including BTN

REQTYP: AB

RPON# 1 = ACT: C

RPON# 2 = ACT: N

Description: Partial Loop disconnect from multiline account that includes disconnect of the BTN \*Requires RPON

| <b>Field</b> | <b>Data Description</b>     | <b>Field Entry</b>        |
|--------------|-----------------------------|---------------------------|
| LNA          | Line Activity               | D                         |
| ECCKT        | Exchange Company Circuit ID | 11/ARSU/111111/ /GTEW     |
| SYSID        | System Identification       | <> (See Footnote 3)       |
| Chanpair     | Channel Pair                | <> (See Footnote 3)       |
| SHELF        | Shelf                       | <ABC017> (See Footnote 3) |
| SLOT         | Slot                        | <010> (See Footnote 3)    |

---



## UNE LSR Order Samples

Partial Loop Disconnect Including BTN

REQTYP: AB

RPON# 1 = ACT: C

RPON# 2 = ACT: N

Description: Partial Loop disconnect from multiline account that includes disconnect of the BTN \*Requires RPON

| Field  | Data Description                   | Field Entry                                    |
|--|------------------------------------|--|
| <b>RPON #2 assignment of new BTN circuit</b> |                                    |  |
| <b>LSR Form</b>                              |                                    |  |
| CCNA   | Customer Carrier Name Abbreviation | <ZTK>  |
| PON  | Purchase Order Number              | <Your PON>                                     |
| VER  | Version                            | <00>   |
| LOCQTY                                       | Location Quantity                  | <001>  |
| DDD  | Desired Date Due                   | <20160612>                                     |
| REQTYP                                       | Request Type                       | AB   |
| SLI  | Sub Loop Indicator                 | S  |
| ACT  | Activity                           | N  |
| AGAUTH                                       | Agency Authorization Status        | Y  |
| ACTL   | Access Customer Terminal Location  | <CLEC CLLI>                                    |
| LSO  | Local Serving Office               | <562325>                                       |
| TOS  | Type of Service                    | <12F1> (See Footnote 1)                        |
| NC   | Network Channel Code               | LX-- (See Footnote 2)                          |
| NCI  | Network Channel Interface Code     | 02QC2.OOF (See Footnote 2)                     |
| <b>NOR</b>                                   | <b>Number of Requests</b>          | <b>0202 (See Footnote 4)</b>                   |
| <b>RPON</b>                                  | <b>Related Pon</b>                 | <b>sample1 (See Footnote 4)</b>                |
| <b>RPVER</b>                                 | <b>Related Pon Version</b>         | <b>01 (See Footnote 4)</b>                     |
| INIT   | Initiator Name                     | <Initiator Name>                               |
| TEL NO                                       | Initiator Telephone Number         | <9192257998>                                   |
| IMPCON                                       | Implementation Contact             | <Mary Williams>                                |
| TEL NO                                       | Telephone Number                   | <8134383000>                                   |
| <b>REMARKS</b>                               | <b>Remarks for RPON#2 Order</b>    | <b>Not a New Install - New BTN Change Only</b> |
| <b>EU Form</b>                               |                                    |  |
| LOCNUM                                       | Location Number                    | <001>  |
| NAME   | End User Name                      | <Our Business Rules>                           |
| AFT  | Address Format Type                | <N if normal, C if assigned house number>      |
| SANO   | Service Address Number             | <14917>  |
| SASN   | Service Address Street Name        | <Musketeer>                                    |
| SATH   | Service Address Street Type        | <RD>   |
| CITY   | City                               | <Anytown>                                      |
| STATE  | State/Province                     | <CA>   |
| ZIP  | Zip/Postal Code                    | <12345>  |
| LCON   | Local Contact                      | <Jane Doe>                                     |
| TEL NO                                       | Local Contact Telephone Number     | <5623259999>                                   |
| <b>LS Form</b>                               |                                    |  |
| <b>Administrative</b>                        |                                    |  |
| LQTY   | Loop Quantity                      | <2>  |
| <b>Service Detail (SD1)</b>                  |                                    |  |
| LOCNUM                                       | Location Number                    | <001>  |



## UNE LSR Order Samples

Partial Loop Disconnect Including BTN

REQTYP: AB

RPON# 1 = ACT: C

RPON# 2 = ACT: N

**Description: Partial Loop disconnect from multiline account that includes disconnect of the BTN \*Requires RPON**

| Field   | Data Description                   | Field Entry                                   |
|---|------------------------------------|---|
| LNUM  | Line Number                        | <00001>                                       |
| LNA   | Line Activity                      | N   |
| <b>CKR</b>  | <b>Circuit Reference</b>           | <b>2090611111 (See Footnote 5)</b>            |
| <b>ECCKT</b>  | <b>Exchange Company Circuit ID</b> | <b>1//ARSU/111112/ /GTEW (See Footnote 5)</b> |
| SYSID   | System Identification              | <> (See Footnote 3)                           |
| Chanpair  | Channel Pair                       | <> (See Footnote 3)                           |
| SHELF   | Shelf                              | <ABC018> (See Footnote 3)                     |
| SLOT  | Slot                               | <010> (See Footnote 3)                        |
| <b>Service Detail (SD2)</b>   |                                    |   |
| LOCNUM  | Location Number                    | <001>   |
| LNUM  | Line Number                        | <00001>                                       |
| LNA   | Line Activity                      | N   |
| <b>CKR</b>  | <b>Circuit Reference</b>           | <b>2090611112 (See Footnote 5)</b>            |
| <b>ECCKT</b>  | <b>Exchange Company Circuit ID</b> | <b>1//ARSU/111113/ /GTEW (See Footnote 5)</b> |
| SYSID   | System Identification              | <> (See Footnote 3)                           |
| Chanpair  | Channel Pair                       | <> (See Footnote 3)                           |
| SHELF   | Shelf                              | <ABC019> (See Footnote 3)                     |
| SLOT  | Slot                               | <010> (See Footnote 3)                        |
| <b>Footnotes:</b>   |                                    |   |
| 1. Use appropriate codes - Reference LSR Type of Service Codes  |                                    |   |
| 2. Use appropriate codes - Reference NC/NCI Matrix  |                                    |   |
| 3. Use the Business Rules to populate the appropriate fields for providing CFA                                    |                                    |   |
| 4. Use the Business Rules to populate the appropriate fields for creating an RPON relationship                    |                                    |   |
| 5. The ECCKT and Circuit Reference (CKR) (FICT TNs) should be provided to ensure proper rearrangement for billing |                                    |   |