



## UNE LSR Order Samples

Loop with LNP

REQTYP: BB

ACT: V

**Description: Loop with Number Portability to 2-Wire Digital Loop (ARSU)**

| Field  | Data Description                   | Field Entry                |
|--|------------------------------------|----------------------------|
| <b>Local Service Request Form (LSR)</b>                |                                    |                            |
| CCNA   | Customer Carrier Name Abbreviation | <ZTK>                      |
| PON  | Purchase Order Number              | <Your PON>                 |
| VER  | Version                            | <01>                       |
| LOCQTY   | Location Quantity                  | <001>                      |
| D/TSENT  | Date and Time Sent                 | <201006070800>             |
| DDD  | Desired Date Due                   | <20100612>                 |
| REQTYP   | Request Type                       | BB                         |
| SLI  | Sub Loop Indicator                 | S                          |
| ACT  | Activity                           | V                          |
| AGAUTH   | Agency Authorization Status        | Y                          |
| ACTL   | Access Customer Terminal Location  | <CLEC CLLI>                |
| LSO  | Local Serving Office               | <203383>                   |
| TOS  | Type of Service                    | 12F1 (See Footnote 1)      |
| NC   | Network Channel Code               | LX-N (See Footnote 2)      |
| NCI  | Network Channel Interface Code     | 02QB9.00A (See Footnote 2) |
| SECNCI   | Secondary Network Channel Code     | <02LS2> (See Footnote 2)   |
| NNSP   | New Network Service Provider       | 1234                       |
| NPDI   | Number Portability Direction       | <D>                        |
| INIT   | Initiator Name                     | Jane Doe                   |
| TEL NO   | Initiator Telephone Number         | 9192257998                 |
| <b>End User Form (EU)</b>                              |                                    |                            |
| LOCNUM   | Location Number                    | <001>                      |
| NAME   | End User Name                      | <Our Business Rules>       |
| AFT  | Address Format Type                | <N>                        |
| SANO   | Service Address Number             | <14917>                    |
| SASN   | Service Address Street Name        | <Musketeer>                |
| SATH   | Service Address Street Type        | <RD>                       |
| CITY   | City                               | <Anytown>                  |
| STATE  | State/Province                     | <OR>                       |
| ZIP  | Zip/Postal Code                    | <33618>                    |
| EATN   | Existing Account Telephone Number  | 2033831212                 |
| ELT  | End User Listing Treatment         | <B>                        |
| LCON   | Local Contact                      | Jane Doe                   |
| TEL NO   | Local Contact Telephone Number     | <2035551212>               |
| <b>Loop Service win Number Portability Form (LSNP)</b> |                                    |                            |
| <b>Administrative</b>                                  |                                    |                            |
| LQTY   | Loop Quantity                      | 1                          |
| NPQTY  | Number Port Quantity               | 1                          |
| <b>Service Detail (SD1)</b>                            |                                    |                            |
| LOCNUM   | Location Number                    | <001>                      |
| LNUM   | Line Number                        | <00001>                    |



## UNE LSR Order Samples

Loop with LNP

REQTYP: BB

ACT: V

Description: Loop with Number Portability to 2-Wire Digital Loop (ARSU)

| <b>Field</b>  | <b>Data Description</b> | <b>Field Entry</b>        |
|---|-------------------------|---------------------------|
| LNA   | Line Activity           | V                         |
| CKR   | Circuit Reference       | <> (See Footnote 4)       |
| System ID   | System Identification   | <> (See Footnote 3)       |
| Chanpair  | Channel Pair            | <> (See Footnote 3)       |
| SHELF   | Shelf                   | <ABC017> (See Footnote 3) |
| SLOT  | Slot                    | <100> (See Footnote 3)    |
| Ported NBR  | Ported Number           | 5033831212                |
| NPT   | Number Portability Type | <D>                       |
| <b>Footnotes:</b>   |                         |                           |
| 1. Use appropriate TOS Values for Business or Residence service.              |                         |                           |
| 2. Use appropriate NC/NCI/SECNCI where applicable at State/Tariff Level       |                         |                           |
| 3 Use the Business Rules to populate the appropriate fields for providing CFA |                         |                           |
| 4. Circuit Reference is Optional and CLEC Assigned                            |                         |                           |