



# DS1 NC/NCI/SECNCI Combinations

## Contents

Purpose	2
DS1 Commonly Used NC/NCI/SECNCI Codes	3
Change Log	4

Effective Date: 05/01/2020

Revised Date:

## Purpose

The purpose of the job aid is to provide commonly used NC/NCI/SECNCI combinations to assist with ordering of the DS1 products.

## DS1 Commonly Used NC/NCI/SECNCI Codes

Table Legend:

AC = Access Customer

CO = Central Office

EU = End User

@ = Protocol codes DS and DU; when used with DS1 service, the DS code is only applied at POP location, the DU code is only applied at an End User location.

Service Description	NC	Option	NCI	SECNCI
1.544 Mbps DS1SF & AMI	HC--	AC - EU	04DS9.15 04DS6.44 (w/CFA)	04DU9.BN
		AC - CO	04DS9.15 04DS6.44 (w/CFA)	04QB9.11 (Collocated)
		CO - EU	04QB9.11(Collocated) 04QB6.33(Collocated w/CFA)	04DU9.BN
		EU - EU	04DU9.BN 04DS6.44 (w/CFA)	04DU9.BN
1.544 Mbps DS1 SF & AMI (CO MUX)	HC-G	AC - CO	04DS9.15 04DS6.44 (w/CFA)	None
		EU - CO	04DU9.BN	None
1.544 Mbps DS1 SF & AMI (CO MUX)	HC-M	AC - CO	04DS9.15 04DS6.44 (w/CFA)	None
1.544 Mbps DS1 ANSI ESF & AMI	HCD-	AC - EU	04DS9.1K	04DU9.1KN
		AC - CO	04DS9.1K	04QB9.11 (Collocated)
		EU - CO	04DU9.1KN	04QB9.11 (Collocated) 04QB6.33 (Collocated w/CFA)
		EU - EU	04DU9.1KN	04DU9.1KN 04DS6.44 (w/CFA)
1.544 Mbps DS1 ANSI ESF & B8ZS	HCE-	AC - EU	04DS9.1S	04DU9.1SN
		AC - CO	04DS9.1S	04QB9.11 (Collocated)
		CO - EU	04QB9.11 (Collocated)	04DU9.1SN
		EU - EU	04DU9.1SN	04DU9.1SN 04DS6.44 (w/CFA)
1.544 Mbps DS1 ANSI ESF/B8ZS/MUX	HCEM	AC - CO	04DS9.15	None
		EU - CO	04DU9.1SN	None
1.544 Mbps DS1 ANSI ESF/B8ZS/MUX (Analog Voice Only)	HCEG	AC - CO	04DS9.15	None
		EU - CO	04DU9.1SN	None
1.544 Mbps DS1 w/Switch Port Term. - SF & AMI	HC-D	AC - CO	04DS9.15	None
		EU - CO	04DU9.BN	None
1.544 Mbps DS1 w/Switch Port Term. - SF & AMI SS7 Dedicated	HC-H	AC - CO	04DS9.15	None
		EU - CO	04DU9.BN	None
1.544 Mbps DS1 w/Switch Port Term. - ESF & AMI SS7 Dedicated	HCDH	AC - CO	04DS9.1K	None
		EU - CO	04DU9.1KN	None

## Change Log

Date	Page Number	Change