



Switched Access – Change to existing SS7 Links REQTYP L, ACT C

VFO Product CCS Links

Date	Revision
5/1/2020	New

Valid ICSC Codes Include: FV03

001 - Access Service Request (ASR)

Administrative Section

Field	Description	Example
CCNA	Customer Carrier Name Abbreviation	XXX (Identifies the IAC Code of the Carrier)
PON	Purchase Order Number	alpha/numeric Note: This Field is Controlled by Customer
VER	Version Identification	alpha/numeric Note: This Field is Controlled by Customer
ICSC	Interexchange Customer Service Center	FV03
D/TSENT	Date and Time Sent	mmddyy and hour, minute & AM or PM
DDD	Desired Due Date	mmddyy
REQTYP	Requisition Type and Status	LD
ACT	Activity	C
LATA	Local Access Transport Area	numeric
RTR	Response Type Requested	alpha/numeric
CUST	Customer Name	optional
UNIT	Unit Identification	C
PIU	Percentage of Interstate Usage	may be blank or may be populated with a numeric
LTP	Local Transport	may be blank, may be populated with N, or may be populated with RF
CKR	Customer Circuit Reference	alpha/numeric
ECCKT	Exchange Company Circuit ID	ID of existing Link (TTD and APZ)
QTY	Quantity	0
BAN	Billing Account Number	may be blank, may be populated with E, or may be populated with existing Link BAN
TSC	Two Six Code	alpha/numeric of existing Link
ACTL	Access Customer Terminal Location	Link ACTL CLLI
REMARKS	Remarks	name of other signaling company, point code of other signaling company, PON of other signaling company

Bill Information

Field	Description	Example
BILLNM	Billing Name	Bill name for ACNA
SBILLNM	Secondary Billing Name	optional
ACNA	Access Customer Name Abbreviation	alpha
STREET (Bill)	Street Address (BILL)	# and street name assigned by US Postal Service
FLOOR (Bill)	Floor (BILL)	optional
ROOM (Bill)	Room (BILL)	optional
CITY (Bill)	City (BILL)	city name for street address
STATE (Bill)	State/Province (BILL)	alpha
ZIP CODE (Bill)	Zip Code (BILL)	numeric
BILLCON	Billing Contact	ACNA contact for billing issues
TEL NO (Bill)	Telephone Number (BILL)	numeric



Contact Information

Field	Description	Example
INIT	Initiator	customer's employee submitting ASR
TEL NO (INIT)	Telephone Number (Initiator)	numeric
INIT FAX NO	Initiator Facsimile Number	optional
INIT EMAIL	Initiator Electronic Mail Address	optional
DSGCON	Design/Engineering Contact	name of customer's designer
TEL NO (DSG CON)	Telephone Number (Design Contact)	numeric
DSG FAX NO	Design Facsimile Number	numeric
STATE (DSG CON)	State/Province (Design Contact)	customer designer's mailing address state
FLOOR (DSG CON)	Floor (Design Contact)	optional
ROOM (DSG CON)	Room (Design Contact)	optional
IMPCON	Implementation Contact	customer's testing contact
TEL NO (IMP CON)	Telephone Number (Implementation Contact)	numeric

004 - Trunking

Service Detail

Field	Description	Example
NC	Network Channel Code	NC of existing Link
NCI	Network Channel Interface Code	NCI of existing Link
CSPC	Customer Signaling Point Code	numeric
SECLOC	Secondary Location	STP CLLI of existing Link

Service Signaling Point Codes

Field	Description	Example
PCACT	Point Code Activity Type	alpha
LT	Link Type	alpha
SLC	Signaling Link Code	numeric
APC	Alias Point Code	optional
TSC2	Two Six Code 2	optional
TSC3	Two Six Code 3	optional
TSC4	Two Six Code 4	optional
SSPC	Service Signaling Point Code	numeric (8 entries allowed per ASR)
SSPC TYPE	Type of Signaling Point Code	alpha (8 entries allowed per ASR)
PCU	Point Code Use	alpha/numeric (8 entries allowed per ASR)
PC TYP	Point Code Type	optional
SSN	Sub System Number	optional
TTN	Translation Type Number	optional
SSPC LOC	Service Signaling Point Code Location	optional
PCNA	Point Code Name Abbreviation	optional

Disclaimer: This is an ASR Sample. There are other ASOG fields not included in this documentation. Please refer to ASOG for all field definitions. You may also reference our Access Custom Business rules.

For further assistance, please contact your Account Manager.