



Switched Access - Disconnect SS7 Links

REQTYP L, ACT D

VFO Product CCS Links

Date	Revision
5/1/2020	New

Valid ICSC Codes Include: FV03

001 - Access Service Request (ASR)

Administrative Section

Field	Description	Example
CCNA	Customer Carrier Name Abbreviation	XXX (Identifies the IAC Code of the Carrier)
PON	Purchase Order Number	alpha/numeric Note: This Field is Controlled by Customer
VER	Version Identification	alpha/numeric Note: This Field is Controlled by Customer
ICSC	Interexchange Customer Service Center	FV03
D/TSENT	Date and Time Sent	mmddy and hour, minute & AM or PM
DDD	Desired Due Date	mmddy
PROJECT	Project Identification	name to be used for all ASRs in the pair or quad
REQTYP	Requisition Type and Status	LD
ACT	Activity	D
RTR	Response Type Requested	alpha/numeric
CUST	Customer Name	optional
UNIT	Unit Identification	C
LTP	Local Transport	may be blank, may be populated with N, or may be populated with RF
CKR	Customer Circuit Reference	customer's ID of link being disconnected
ECCKT	Exchange Company Circuit ID	existing Link ID (TRN/TTD/APZ)
QTY	Quantity	number of layers being disconnected
BAN	Billing Account Number	may be actual Link BAN or E
TSC	Two Six Code	Link being disconnected
ACTL	Access Customer Terminal Location	Link ACTL CLLI
RPON	Related Purchase Order Number	PON of other Link in pair or quad
REMARKS	Remarks	any RPONs in addition to information in the RPON field

Bill Information

Field	Description	Example
BILLNM	Billing Name	Bill name for ACNA
SBILLNM	Secondary Billing Name	optional
ACNA	Access Customer Name Abbreviation	alpha
STREET (Bill)	Street Address (BILL)	# and street name assigned by US Postal Service
FLOOR (Bill)	Floor (BILL)	optional
ROOM (Bill)	Room (BILL)	optional
CITY (Bill)	City (BILL)	city name for street address
STATE (Bill)	State/Province (BILL)	alpha
ZIP CODE (Bill)	Zip Code (BILL)	numeric
BILLCON	Billing Contact	ACNA contact for billing issues
TEL NO (Bill)	Telephone Number (BILL)	numeric



Contact Information

Field	Description	Example
INIT	Initiator	name of customer's employee submitting the ASR
TEL NO (INIT)	Telephone Number (Initiator)	numeric
INIT FAX NO	Initiator Facsimile Number	optional
INIT EMAIL	Initiator Electronic Mail Address	optional
IMP CON	Implementation Contact	customer's testing contact
TEL NO (IMP CON)	Telephone Number (Implementation Contact)	numeric

004 - Trunking

Service Detail

Field	Description	Example
NC	Network Channel Code	NC of Link being disconnected
NCI	Network Channel Interface Code	NCI of Link being disconnected
CFA	Connecting Facility Assignment	ID of highest facility
CSPC	Customer Signaling Point Code	numeric
SCFA	Secondary Connecting Facility Assignment	DS1 ID if CFA is populated
SECLOC	Secondary Location	STP CLLI

Service Signaling Point Code

Field	Description	Example
LT	Link Type	alpha
SLC	Signaling Link Code	numeric

Disclaimer: This is an ASR Sample. There are other ASOG fields not included in this documentation. Please refer to ASOG for all field definitions. You may also reference our Access Custom Business rules.

For further assistance, please contact your Account Manager.