



# Switched Access - FG D Trunks - Disconnect

## REQTYP M, ACT D

### VFO Product Feature Group D

Date	Revision
5/1/2020	New

Valid ICSC Codes Include: FV03

## 001 - Access Service Request (ASR)

### Administrative Section

Field	Description	Example
<b>CCNA</b>	Customer Carrier Name Abbreviation	XXX (Identifies the IAC Code of the Carrier)
<b>PON</b>	Purchase Order Number	alpha/numeric <b>Note:</b> This Field is Controlled by Customer
<b>VER</b>	Version Identification	alpha/numeric <b>Note:</b> This Field is Controlled by Customer
<b>ICSC</b>	Interexchange Customer Service Center	FV03
<b>ACTI</b>	Activity Indicator	depends if full or partial disconnect & how traffic will be routed D = for partial disconnect of trunk group  E = for full disconnect of trunk group with re-routing  F = for full disconnect of trunk group without routing
<b>D/TSENT</b>	Date and Time Sent	mmddyy and hour, minute & AM or PM
<b>DDD</b>	Desired Due Date	mmddyy
<b>REQTYP</b>	Requisition Type and Status	MD
<b>ACT</b>	Activity	D
<b>RTR</b>	Response Type Requested	alpha/numeric
<b>AFO</b>	Additional Forms	required if additional circuit detail screens are necessary
<b>TQ</b>	Translation Questionnaire Request	depends on ACTI entry
<b>UNIT</b>	Unit Identification	C
<b>LTP</b>	Local Transport	depends on facility
<b>CKR</b>	Customer Circuit Reference	customer's ID of trunk(s) being disconnected
<b>ECCKT</b>	Exchange Company Circuit ID	ID of trunk group being disconnected(TRN/TTD/APZ)
<b>QTY</b>	Quantity	number of trunks being disconnected
<b>BAN</b>	Billing Account Number	may be actual trunk BAN or E
<b>TSC</b>	Two Six Code	trunk group being disconnected
<b>ACTL</b>	Access Customer Terminal Location	trunk ACTL CLLI
<b>REMARKS</b>	Remarks	As needed
<b>*</b>	<b>Note:</b>	<b>if ACTI is populated with F, must have Remark of where CIC was previously rerouted</b>



## Bill Information

Field	Description	Example
<b>BILLNM</b>	Billing Name	Bill name for ACNA
<b>SBILLNM</b>	Secondary Billing Name	optional
<b>ACNA</b>	Access Customer Name Abbreviation	alpha
<b>STREET (Bill)</b>	Street Address (BILL)	# and street name assigned by US Postal Service
<b>FLOOR (Bill)</b>	Floor (BILL)	optional
<b>ROOM (Bill)</b>	Room (BILL)	optional
<b>CITY (Bill)</b>	City (BILL)	city name for street address
<b>STATE (Bill)</b>	State/Province (BILL)	alpha
<b>ZIP CODE (Bill)</b>	Zip Code (BILL)	numeric
<b>BILLCON</b>	Billing Contact	employee from ACNA that can be contacted for billing issues
<b>TEL NO (Bill)</b>	Telephone Number (BILL)	numeric

## Contact Information

Field	Description	Example
<b>INIT</b>	Initiator	customer's employee submitting ASR
<b>TEL NO (INIT)</b>	Telephone Number (Initiator)	numeric
<b>INIT FAX NO</b>	Initiator Facsimile Number	optional
<b>INIT EMAIL</b>	Initiator Electronic Mail Address	optional
<b>IMPCON</b>	Implementation Contact	customer's employee submitting ASR
<b>TEL NO (IMP CON)</b>	Telephone Number (Implementation Contact)	numeric

## 004 - Trunking

### Service Detail

Field	Description	Example
<b>NC</b>	Network Channel Code	NC of trunk group being disconnected
<b>NCI</b>	Network Channel Interface Code	NCI of trunk group being disconnected
<b>QACI</b>	Quantity Additional Circuit Information	numeric, if necessary
<b>SECLOC</b>	Secondary Location	end office or tandem CLLI
<b>CFA</b>	Connecting Facility Assignment	ID of highest facility
<b>CIC</b>	Carrier Identification Code	CIC of trunk group being disconnected
<b>HBAN</b>	High Capacity Channel Billing Account Number	facility billing account number
<b>SCFA</b>	Secondary Connecting Facility Assignment	DS1 ID if CFA is populated
<b>MUXLOC</b>	Multiplexing Location	DS3 HUB
<b>RECCKT</b>	Related Exchange Company Circuit Identification	if facility is being disconnected must be populated with DS1
<b>FACTL</b>	Facility Access Customer Terminal Location	if DS1 is being disconnected must be populated



## 019 - Translation Questionnaire (TQ)

### Common Section

Field	Description	Example
*	<b>Note:</b>	<b>The Translation Questionnaire is prohibited if the ACTI is populated with D or F</b>
<b>TECH CON</b>	Customer Technical Contact (Translation)	name
<b>TEL NO (Tech Contact Translation)</b>	Technical Contact Telephone Number (Translation)	numeric
<b>TG ACT</b>	Trunk Group Activity	D
<b>TGTYP</b>	Trunk Group Type	matches type of trunk group being disconnected
<b>TSC</b>	Two Six Code	alpha/numeric
<b>APON</b>	Associated Purchase Order Number	optional
<b>CIP</b>	Carrier Identification Parameter	required
<b>FACT</b>	Feature Activity (ALT REF)	E
<b>ALT REF</b>	Alternate Routing Trunk Group Reference	alpha/numeric

### Trunking Section

Field	Description	Example
<b>CIC</b>	Carrier Identification Code	numeric
<b>ACIC</b>	Additional Carrier Identification Code	required if multiple CICs ride trunk group

Disclaimer: This is an ASR Sample. There are other ASOG fields not included in this documentation. Please refer to ASOG for all field definitions. You may also reference our Access Custom Business rules.

For further assistance, please contact your Account Manager.