

Switched Access - Establish New SS7 Link REQTYP L, ACT N

VFO Product CCS Links

Date	Revision
5/1/2020	New

Valid ICSC Codes Include: FV03

001 - Access Service Request (ASR)

Administrative Section

, .a		
Field	Description	Example
CCNA	Customer Carrier Name Abbreviation	XXX (Identifies the IAC Code of the Carrier)
PON	Purchase Order Number	alpha/numeric
		Note: This Field is Controlled by Customer
VER	Version Identification	alpha/numeric
		Note: This Field is Controlled by Customer
ICSC	Interexchange Customer Service	FV03
D /=====	Center	
D/TSENT	Date and Time Sent	mmddyy and hour, minute & AM or PM
DDD	Desired Due Date	mmddyy
PROJECT	Project Identification	name to be used for all ASRs in the pair or quad
REQTYP	Requisition Type and Status	LD
ACT	Activity	N
LATA	Local Access Transport Area	numeric
RTR	Response Type Requested	alpha/numeric
AFO	Additional Forms	required if QTY greater than 1 and additional circuit detail
		screens necessary
CUST	Customer Name	optional
UNIT	Unit Identification	C
PIU	Percentage of Interstate Usage	numeric
LTP	Local Transport	may be blank, may be populated with N, or may be populated with RF
CKR	Customer Circuit Reference	alpha/numeric
QTY	Quantity	number of layers being installed
BAN	Billing Account Number	may be blank, may be populated with N, or may be populated with existing Link BAN
ACTL	Access Customer Terminal Location	Link ACTL CLLI
RPON	Related Purchase Order Number	PON of other Link in pair or quad
REMARKS	Remarks	what the Links will be used for, other customers involved in the pair or quad, any additional PONs not populated in RPON field

Bill Information

Field	Description	Example
BILLNM	Billing Name	Bill name for ACNA
SBILLNM	Secondary Billing Name	optional
ACNA	Access Customer Name Abbreviation	alpha
STREET (Bill)	Street Address (BILL)	# and street name assigned by US Postal Service
FLOOR (Bill)	Floor (BILL)	optional
ROOM (Bill)	Room (BILL)	optional
CITY (Bill)	City (BILL)	city name for street address
STATE (Bill)	State/Province (BILL)	alpha
ZIP CODE (Bill)	Zip Code (BILL)	numeric
BILLCON	Billing Contact	ACNA contact for billing issues
TEL NO (Bill)	Telephone Number (BILL)	numeric



Contact Information

Field	Description	Example
INIT	Initiator	customer's employee submitting ASR
TEL NO (INIT)	Telephone Number (Initiator)	numeric
INIT FAX NO	Initiator Facsimile Number	optional
INIT EMAIL	Initiator Electronic Mail Address	optional
DSGCON	Design/Engineering Contact	name of customer's designer
TEL NO (DSG CON)	Telephone Number (Design Contact)	numeric
DSG FAX NO	Design Facsimile Number	optional
STREET (DSG CON)	Street Address (Design Contact)	designer's mailing address street
FLOOR (DSG CON)	Floor (Design Contact)	optional
ROOM (DSG CON)	Room (Design Contact)	optional
CITY (DSG CON)	City (Design Contact)	designer's mailing address city
STATE (DSG CON)	State/Province (Design Contact)	alpha
DSG EMAIL	Design Electronic Mail Address	optional
IMPCON	Implementation Contact	customer's testing contact
TEL NO (IMP CON)	Telephone Number (Implementation Contact)	numeric

004 - Trunking

Service Detail

Field	Description	Example
		•
NC	Network Channel Code	See following Note: Note: Customers must refer to iconectiv for accurate NC/NCI/SECNCI combinations
		or refer to the NC/NCI/SECNCI job aid found at
		https://wholesale.ziplyfiber.com/wholesale/access-services/nc-nci-
		secnci-job-aids
NCI	Network Channel Interface	See following Note:
	Code	Note: Customers must refer to iconectiv for accurate NC/NCI/SECNCI combinations or refer to the NC/NCI/SECNCI job aid found at
		https://wholesale.ziplyfiber.com/wholesale/access-services/nc-nci-
		secnci-job-aids
QACI	Quantity Additional Circuit Information	numeric, if necessary
CFA	Connecting Facility Assignment	ID of highest facility
CSL	Customer Switch Location	alpha/numeric CLLI of distant point
CST	Customer Switch Type	type of switch at distant point
CSPC	Customer Signaling Point Code	numeric
SCFA	Secondary Connecting Facility Assignment	DS1 ID if CFA is populated
SECLOC	Secondary Location	STP CLLI

Service Signaling Point Codes

Field	Description	Example
LT	Link Type	alpha
SLC	Signaling Link Code	numeric

Disclaimer: This is an ASR Sample. There are other ASOG fields not included in this documentation. Please refer to ASOG for all field definitions. You may also reference our Access Custom Business rules.

For further assistance, please contact your Account Manager.