



# Local Interconnection Switched Access - Disconnect Trunks

## REQTYP M, ACT D

### VFO Product - Local Trunking Service

Date	Revision
5/1/2020	New

**Note:** Wireless Type 2A Trunks establish connections to the NXX prefixes served by end offices that subtend an Access Tandem connected to the Mobile Telephone Switching Office (MTSO).

**Note:** Wireless Type 2B Trunks establish connections to NXX prefixes service by and end office connected directly to the Mobile Telephone Switching Office (MTSO).

Valid ICSC Codes Include: FV03

## 001 - Access Service Request (ASR)

### Administrative Section

Field	Description	Example
CCNA	Customer Carrier Name Abbreviation	XXX (Identifies the IAC Code of the Carrier)
PON	Purchase Order Number	<b>Note:</b> This Field is Controlled by Customer
VER	Version Identification	<b>Note:</b> This Field is Controlled by Customer
ICSC	Interexchange Customer Service Center	FV03
ACTI	Activity Indicator	D=Partial disconnect of trunk group E=Disconnect trunks and re-route of traffic F=Disconnect trunk group and no reroute of traffic
CC	Company Code	Identifies the customer requesting local service
DDD	Desired Due Date	Standard Interval
REQTYP	Requisition Type and Status	M
ACT	Activity	D
AFO	Additional Forms	Populate with a Y for more than 24 trunks being requested.
TQ	Translation Questionnaire Request	Required if ACTI = E
LTP	Local Transport	Required
CKR	Customer Circuit Reference	Customer Circuit ID
QTY	Quantity	number of trunks being disconnected
BAN	Billing Account Number	Entry of "E" for existing BAN
ECCKT	Exchange Company Circuit ID	Circuit ID of trunks being disconnected
ACTL	Access Customer Terminal Location	trunk ACTL CLLI
RPON	Related Purchase Order Number	If necessary
REMARK	Remarks	Disconnect trunks and any other information you would like.
S		



## Bill Information

Field	Description	Example
BILLNM	Billing Name	bill name for ACNA
SBILLNM	Secondary Billing Name	optional
ACNA	Access Customer Name Abbreviation	alpha
TE	Tax Exemption	alpha
FUSF	Federal Universal Service Fee	E or N <b>Note:</b> Refer to the ASOG FUSF field Notes for Assessed or Exempted rules
STREET (Bill)	Street Address (BILL)	# and street name assigned by US Postal Service
FLOOR (Bill)	Floor (BILL)	optional
ROOM (Bill)	Room (BILL)	optional
CITY (Bill)	City (BILL)	city name for street address
STATE (Bill)	State/Province (BILL)	alpha
ZIP CODE (Bill)	Zip Code (BILL)	numerics
BILLCON	Billing Contact	employee from ACNA that can be contacted for billing issues
TEL NO (Bill)	Telephone Number (BILL)	numerics

## Contact Information

Field	Description	Example
INIT	Initiator	customer's employee submitting ASR
TEL NO (INIT)	Telephone Number (Initiator)	numerics
INIT FAX NO	Initiator Facsimile Number	optional
INIT EMAIL	Initiator Electronic Mail Address	optional
DSGCON	Design/Engineering Contact	name of customer's designer
TEL NO (DSG CON)	Telephone Number (Design Contact)	numeric
DSG FAX NO	Design Facsimile Number	optional
STREET (DSG CON)	Street Address (Design Contact)	customer designer's mailing address street
FLOOR (DSG CON)	Floor (Design Contact)	optional
ROOM (DSG CON)	Room (Design Contact)	optional
CITY (DSG CON)	City (Design Contact)	customer designer's mailing address city
STATE (DSG CON)	State/Province (Design Contact)	alpha
ZIP CODE (DSG CON)	Zip Code (Design Contact)	numerics
DSG EMAIL	Design Electronic Mail Address	optional
IMP CON	Implementation Contact	customer's testing contact
TEL NO (IMP CON)	Telephone Number (Implementation Contact)	numerics
D/TREC	Date and Time Received	mmddyy and hour, minute & AM or PM



## 004 - Trunking

### Service Detail

Field	Description	Example
NC	Network Channel Code	NC code of existing trunks <b>Note:</b> Customers must refer to iconectiv for accurate NC/NCI/SECNCI combinations <b>or</b> refer to the NC/NCI/SECNCI job aid found at <a href="https://wholesale.ziptyfiber.com/wholesale/access-services/access-reference-documents">https://wholesale.ziptyfiber.com/wholesale/access-services/access-reference-documents</a>
NCI	Network Channel Interface Code	See following Note: <b>Note:</b> Customers must refer to iconectiv for accurate NC/NCI/SECNCI combinations <b>or</b> refer to the NC/NCI/SECNCI job aid found at <a href="https://wholesale.ziptyfiber.com/wholesale/access-services/access-reference-documents">https://wholesale.ziptyfiber.com/wholesale/access-services/access-reference-documents</a>
SECLOC	Secondary Location	end office or tandem CLLI
CFA	Connecting Facility Assignment	ID of highest level facility
TTT	Transport Trunk Termination Code	numeric
QACI	Quantity Additional Circuit Information	Only required if more than 24 trunks requested
RECCKT	Related Exchange Company Circuit	DS1 to be disconnected if trunks and T1s to be disconnected
TCIC	Trunk Circuit Identification Code	required if SS7

## 019 - Translation Questionnaire (TQ) (Only used when ACTI=E)

### Common Section

Field	Description	Example
TECH CON	Customer Technical Contact (Translation)	customer's Translations tester
TEL NO (Tech Contact Translation)	Technical Contact Telephone Number (Translation)	numerics
TG ACT	Trunk Group Activity	D=Disconnect trunk group
TGTYP	Trunk Group Type	Required entry when disconnecting existing trunk group
TSC	Two Six Code	ACTI=E need to give new TSC traffic to be routed to when this group is disconnected
ALT REF	Alternate Routing Trunk Group Reference	Optional field entry when disconnecting a trunk group
REMARKS	Remarks	Communicate to the Routing Group the specifics of your order request.



## Interconnection Translation Routing

Field	Description	Example
TTEST TN	Translations Test Telephone Number (NPA/NXX)	585-123-4567
TECH CON	Customer Technical Contact (Translation)	John Smith
TEL NO (Tech Contact Translation)	Technical Contact Telephone Number (Translation)	585-555-6789
TTEST RESP	Translations Test Response (NPA/NXX)	Milliwatt Tone
C.NPA/NXX (1)	Local Exchange Customer NPA/NXX	Input all codes that will be disconnected or rerouted from this trunk group. Use additional fields if needed.

## 007 - Additional Circuit Information (ACI)

### Circuit Details

Field	Description	Example
REF NUM (1)	Reference Number	For every DS1 ordered, an ACI page must accompany the request.
CFA	Connecting Facility Assignment	1 0 1 / T 1 / 3 / ROCH
TRN	Trunk Number	Prohibited if TCIC is populated
HBAN	High Capacity Channel Billing Account Number	E
TCIC	Trunk Circuit Identification Code	Required if disconnecting SS7 trunks
RECCKT (1)	Related Exchange Company Circuit Identification	Populate T1 that is to be disconnected same time the trunks are being disconnected.
CKR	Customer Circuit Reference	Customer circuit ID

Disclaimer: This is an ASR Sample. There are other ASOG fields not included in this documentation. Please refer to ASOG for all field definitions. You may also reference our Access Custom Business rules.

For further assistance, please contact your Account Manager.