



ATM NC/NCI/SECNCI Combinations

Contents

Purpose	2
FV03 OR, WA, ID, MT	3
Change Log	5

Jurisdiction: FV03
Revised Date: 5/1/2020

Purpose

The purpose of the job aid is to provide commonly used NC/NCI/SECNCI combinations to assist with ordering of the Asynchronous Transfer Mode (ATM) product.

FV03 OR, WA, ID, MT

Applies to:

FV03

UNI –User to Network Interface

Table Legend:

AC = Access Customer

CO = Central Office

EU = End User

COLO = Collocation

* The option is identified with one of the following option codes:

B – ANSI: Long Reach-1, Single Longitudinal Mode Laser, 1310 nm

D – ANSI: Intermediate Reach-1, Single Longitudinal Mode Laser, 1310 nm

F – ANSI: Short Reach-1, Multi Longitudinal Mode Laser, 1310 nm

X – Provider Engineered Reach Factor

Service Description	NC	A - Z Location	NCI	SECNCI
UNI				
DS1 UNI	HCE6	AC-CO	04DS9.1S 04DS6.44 02/04SOF.*	04CX9
		EU-CO	04DU9.1SN 04DS6.44 02/04SOF.*	04CX9
		COLO-CO	04QB9.11 04QB6.33 02/04QBF.LL	04CX9
DS1 UNI Port Only	SNDA	CO-CO	04QB9.11 04QB6.33 02/04QBF.LL	04CX9
DS3 UNI	HF-6	AC-CO	04DS6.44 02/04SOF.*	04CX6.3
		EU-CO	04DS6.44 02/04SOF.*	04CX6.3
		COLO-CO	04QB6.33 02/04QBF.LL	04CX6.3
DS3 UNI C-Bit Parity	HFC6	AC-CO	04DS6.44A 02/04SOF*	04CX6.3
		COLO-CO	04QB6.33 02/04QBF.L	04CX6.3
DS3 UNI Port Only	SNDB	CO-CO	04QB6.33 02/04QBF.LL	04CX6.3
OC3c UNI	OB-6	AC-CO	02SOF*	02CXF.A
		EU-CO	02SOF*	02CXF.A
		COLO-CO	02/04QBF.LL	02CXF.A
OC3c UNI Port Only	SNDC	CO-CO	02/04QBF.LL	02CXF.A
OC12c UNI	OD-6	AC-CO	02/04SOF*	02CXF.B
		EU-CO	02/04SOF*	02CXF.B
		COLO-CO	02/04SOF*	02CXF.B
OC12c UNI Port Only	SNDD	CO-CO	02/04QBF.LL	02CXF.B

NNI – Network to Network Interface

Service Description	NC	A - Z Location	NCI	SECNCI
NNI				
DS1 NNI	HCEJ	AC-CO	04DS9.1S 04DS6.44 02/04QBF.LL	04CX9
		COLO-CO	04QB9.11 04QB6.33 02/04QBF.LL	04CX9
DS1 NNI Port Only	SNEA	CO-CO	04QB9.11 04QB6.33 02/04QBF.LL	04CX9
DS3 NNI	HF-J	AC-CO	04DS6.44 02/04SOF.*	04CX6.3
		COLO-CO	04QB6.33 02/04QBF.LL	04CX6.3
DS3 NNI C-Bit Parity	HFCJ	AC-CO	04DS6.44A 02/04SOF.*	04CX6.3
		COLO-CO	04QB6.33 02/04QBF.LL	04CX6.3
DS3 NNI Port Only	SNEB	CO-CO	04QB6.33 02/04QBF.LL	04CX6.3
OC3c NNI	OB-P	AC-CO	02/04SOF.*	02CXF.A
		COLO-CO	02/04SOF.*	02CXF.A
OC3c NNI Port Only	SNEC	CO-CO	02/04QBF.LL	02CXF.A
OC12c NNI	OD-P	AC-CO	02/04SOF.*	02CXF.B
		COLO-CO	02/04QBF.LL	02CXF.B
OC12c NNI Port Only	SNED	CO-CO	02/04QBF.LL	02CXF.B

Change Log

Date	Page Number	Change